



BSPH SH-616L

Intelligent & Fashion

Email : saLes2@bsphpa.com

http://en.bsphpro.com/

SH-616L

BSPH Home Audio Systems



Features

- 13.2 Inch true color, graphical interfaces, Chinese and English language selectable.
2. Full touch screen design.
3. Song, track, LRC, audio source are displayed in the screen.
4. Independent control in volume, treble and bass.
- 5.6 audio sources for different programs, built in SD,USB socket, FM/AM and Bluetooth module, and three way external audio sources can be controlled equally as they are built inside.
6. Wireless control, by connecting the router with the host machine, then the smart phone can be searching for the wifi signal of the host machine to realize smart control.
7. Built in newest 4.0 Bluetooth module, which can receive the Bluetooth signal of the Bluetooth device to realize music wireless playing
8. HIFI stereo sound output, the music of all zones can be played independently at the same time.
9. Rated power: 480 W, 12 zones with 2*20 watts, other 4 zones are allowed to be connected external amplifier (no power limits) for larger rooms.
10. 8 ohms output.
11. Wall-in style installation, both Star wire and Hand-in-Hand wire are available;
12. MP3 player supports single, single repeat, all and all repeat these four play modes
13. Timer function, each zone can pre-edit 99 programs one day as reminder for special day and unique thing.
14. Alarm function, six available terminals can be triggered by the short circuit signal and then alarm in all zones, such as gas leak, door bell and so on.
15. Abide by Rs-232 communication protocols can be central controlled with other home appliance.
16. Various HIFI speakers can be selectable.

Specifications

Model	SH-616L
Output Power	480W
Input sensitivity	0.75V 0dBV
Damping factor	500
SNR	Less than 75
Frequency response	20Hz-0kHz +3dB
Am frequency band	522Hz-1611MHZ
Stepping	9KHz
FM frequency band	87KHz-108KHz
Stepping	50KHz
THD	<0.6%
Rising Speed	70V/MS
Cooling method	Forced air cooling
Protection	Power,overheat, overload,short circuit
Power	-220V / + 10% 50Hz
Power Consumption	Max 550W
Size	430X375X145MM



HIFI speaker Six audio sources Bluetooth Smart alarming 16 zones selection



SH-616L rear



SH-618



* Matched with SH-616L

Features

Specifications



1. Built in 4 channels amplifier matrix , 4 inputs for audio source and 4 output;
2. Can be connected with 4 ohms and 8 ohms speaker: output power of 4 ohms: 50W*4*2 output power of 8 ohms: 35W*4*2
3. Support bridge connection;
4. Energy conservation, without operation during ten minutes, the device will be automatically entered into sleeping mode, and its 2nd power management can control the power consumption so that can lengthen the working life

Rated output power	8Ω/35W*2X4 4Ω/50W*2X4
Input sensitivity	0.775V 0dB
Damping factor	>200
SNR	>80dB
Frequency response	20Hz-20KHz ±3dB
THD	<0.5%
Rising speed	30V/us
Cooling method	Forced air cooling
Protection	Power, oveheat, overload, short circuit
Power	~ 220V/±10% 50Hz
Power consumption	450W
Size	400×430×60mm
Weight	8.8Kg



SH-616L One host machine, 16 zones, music and security are all in control!

